



90-265Vac via Powecon HC
 Amplifier Net Weight 20 Lb (11.9 kg)

RMS Control Port can jumper through up to 3 amplifiers

Included Accessories

NAC3FC-HC Powercon HC Cable End Connector

Optional Accessories

- Cable-PCHC-5ft-240V Power Cable Powercon HC to L6-20
- Cable-PCHC-5ft-120V Power Cable Powercon HC to 5020P
- Custom Cable connection can be ordered on request
- RRR-1 Rear Rack Rail Support Kit
- AMP-FILTER-1 RMS-Amplification Washable Replacement Filter

DETAILS: DIMENSIONS ARE IN INCHES TOLERANCES: LINEAR ± 0.03 MACH ANGULAR ± 0.5° BEND ANGULAR ± 1°		THE INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF RMS-ACOUSTICS . ANY COPY OR REPRODUCTION OF THIS DOCUMENT IN PART OR AS A WHOLE FOR THE BASIS OF MANUFACTURE OR SALE OF ANY ITEM OR APPARATUS DESCRIBED HEREIN WITHOUT WRITTEN AUTHORIZATION FROM RMS-ACOUSTICS IS PROHIBITED. DO NOT SCALE DRAWING			RMS ACOUSTICS WWW.RMS-ACOUSTICS.COM 13720 24TH ST E UNIT E110 SUMNER, WA 98390	
APPROVALS DRAWN: Ryan McCauley CHECKED:		DATE 7/11/2023	PROJECT RMS-10KD Mechanical Drawing		SIZE B	REV A
		1/1	SCALE 1:4	7/11/2023		