



90-265Vac via Powecon HC
 Amplifier Net Weight 20 Lb (11.9 kg)

RMS Control Port can jumper through up to 3 amplifiers

Included Accessories
 NAC3FC-HC Powercon HC Cable End Connector

Optional Accessories
 Cable-PCHC-5ft-240V Power Cable Powercon HC to L6-20
 Cable-PCHC-5ft-120V Power Cable Powercon HC to 5020P
 Custom Cable connection can be ordered on request
 RRR-1 Rear Rack Rail Support Kit
 AMP-FILTER-1 RMS-Amplification Washable Replacement Filter

DETAILS: DIMENSIONS ARE IN INCHES TOLERANCES: LINEAR ± 0.03 MACH ANGULAR ± 0.5° BEND ANGULAR ± 1°		THE INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF RMS-ACOUSTICS . ANY COPY OR REPRODUCTION OF THIS DOCUMENT IN PART OR AS A WHOLE FOR THE BASIS OF MANUFACTURE OR SALE OF ANY ITEM OR APPARATUS DESCRIBED HEREIN WITHOUT WRITTEN AUTHORIZATION FROM RMS-ACOUSTICS IS PROHIBITED. DO NOT SCALE DRAWING			RMS ACOUSTICS WWW.RMS-ACOUSTICS.COM 13720 24TH ST E UNIT E110 SUMNER, WA 98390	
APPROVALS	DATE	PROJECT	SCALE	DATE	SIZE	REV
DRAWN: Ryan McCauley CHECKED:	7/11/2023	RMS-20KD Mechanical Drawing	1/1 SCALE 1:4	7/11/2023	B	A