



90-265Vac via Powercon
Amplifier Net Weight 16 Lb (7.3 kg)

RMS Contol Port can jumper through up to 3 amplifiers

Included Accessories

NAC3FCA Powercon Cable End Connector

Optional Accessories

Cable-PC-5ft-240V Power Cable Powercon HC to L6-20

Cable-PC-5ft-120V Power Cable Powercon HC to 5-20P

Custom Cable connection can be ordered on request

RRR-1 Rear Rack Rail Support Kit

AMP-FILTER-1 RMS-Amplification Washable Replacement Filter

DETAILS:

DIMENSIONS ARE IN INCHES
TOLERANCES:
LINEAR ± 0.01
MACH ANGULAR $\pm 0.5^\circ$
BEND ANGULAR $\pm 1^\circ$

THE INFORMATION CONTAINED IN THIS DOCUMENT IS THE SOLE PROPERTY OF **RMS-ACOUSTICS**. ANY COPY OR REPRODUCTION OF THIS DOCUMENT IN PART OR AS A WHOLE FOR THE BASIS OF MANUFACTURE OR SALE OF ANY ITEM OR APPARATUS DESCRIBED HEREIN WITHOUT WRITTEN AUTHORIZATION FROM **RMS-ACOUSTICS** IS PROHIBITED.
DO NOT SCALE DRAWING

RMS
ACOUSTICS

WWW.RMS-ACOUSTICS.COM

13720 24TH ST E

UNIT E110

SUMNER, WA 98390

APPROVALS		DATE	PROJECT		SIZE	REV
DRAWN: Ryan McCauley		8/23/2023	RMS-410KiD Mechanical Drawing		B	A
CHECKED:			1/1	SCALE 1:4	8/23/2023	